



Qr Pro 10w Compatible Dimmers

	Quantity	Result	Observation	Acoustics	Qty	Comments
Dimmer	Hamilton Verve HM2031	✓	100-10% Smooth Dim	Noise Free	Up to 10	Recommended
	Hamilton LEDITB100	✓	100-20% Smooth Dim	Noise Free	Up to 10	Recommended
	Zano ZGRID150	✓	96-10% Smooth Dim	Noise Free	Up to 16	Recommended
	Zano ZGRID250	✓	96-20% Smooth Dim	Noise Free	Up to 25	Recommended
	Zano ZSMART	✓	70-0% Smooth Dim	Noise Free	2-16	Recommended
	Zano ZBARLED300	✓	100-0% Smooth Dim	Noise Free	Up to 25	Recommended
	Deta G3522	✓	100-10% Smooth Dim	Constant buzzing if more than 10 fittings are connected	Up to 10	Recommended
	Newlec NLSSL8307	✓	100-10% Smooth Dim, can flicker at low level but settles after a few seconds	Faint Buzzing from driver	Up to 15	Recommended
	Newlec NL8806WA	✓	90%-Off Smooth Dim	Noise Free	Up to 20	Recommended
	Varilight V-PRO JP250-P	✓	100-5% Smooth Dim	Noise Free	Up to 20	Recommended
	Varilight V-PRO GJP100W	✓	100-10% Smooth Dim	Faint Buzzing from driver	Up to 15	Recommended

Please Note: KSR test these dimmers singularly please consult the dimmer manufacturer for recommendations on other scenarios. All recommendations are correct as per the date tested below. KSR cannot be held responsible for any changes in the dimmer specification.

