



QR10 Compatible Dimmers

Dimmer	Quantity	Result	Observation	Acoustics	Qty	Comments
	Hamilton Verve HM2031	✓	100-10% Smooth Dim	Noise Free	Up to 20	Recommended
	Hamilton LED IT-B100	✓	100-10% Smooth Dim	Noise Free	Up to 10	Recommended
	Hamilton 7W1X100 LED	✓	100-10% Incremental Dim	Noise Free	Up to 10	Recommended
	Zano ZMC150	✓	100-0% Smooth Dim	Noise Free	Up to 15	Recommended
	Newlec NL8306/12	✓	100-10% Smooth Dim	Noise Free	Up to 20	Recommended
	Newlec NL8806W	✓	100-5% Smooth Dim	Noise Free	Up to 20	Recommended
	Newlec NL8806WA	✓	100-10% Smooth Dim	Noise Free	Up to 20	Recommended
	Varilight V-PRO GJP100W	✓	100-10% Smooth Dim if fittings are powered off at 25% dimmer will not power lights back on until dimming level increased	Noise Free	Up to 10	Recommended
	Varilight V-PRO JQP401	✓	100-5% Smooth Dim if fittings are powered off at 25% dimmer will not power lights back on until dimming level increased	Noise Free	Up to 20	Recommended
	Schneider Lisse GGBL6012	✓	100-10% Smooth Dim	Noise Free	Up to 20	Recommended

Please Note: KSR test these dimmers singularly please consult the dimmer manufacturer for recommendations on other scenarios.
All recommendations are correct as per the date tested below. KSR cannot be held responsible for any changes in the dimmer specification.