Installation Sheet) KSR7192

Read these instructions before commencing installation & retain them for future reference.

IP44 ⊕ **(** € (]0.5m | 240 V 9 W

These fittings are Class I and must be Earthed

Important Information

It is recommended that luminaires are installed and fitted by a qualified electrician ensuring the installation complies with current IEE wiring regulations & local building control. These products are designed for connection to a 240V 50Hz supply. Any broken or damaged parts should be replaced as soon as possible. KSR will not accept responsibility for any claims arising from a poor installation.

General Maintenance

General maintenance and cleaning should be performed at least quarterly. Clean product outer using a damp cloth. After any maintenance, remember to check all seals are intact.

Installation Procedure

Familiarize yourself with the fixture, wind back the grub screw that secures the main fitting to the mounting plate.


Set grub screw back enough to allow the base plate to come away from the body.

Offer the base plate up to a suitable surface and mark atleast two fixing points, ensuring the cable entry is towards the bottom of the plate. Once drilled, dress the mains supply cable through the grommet and secure to the wall. To make installation easier remove the rubber grommet from the housing.

Terminate the fixed wiring into the terminal block, following the guide below and/or the markings on the fitting.

Ensure the main gasket is seated correctly on the base plate and place the fitting onto it, over up the fitting to the base plate, tighten the grub screw ensuring the seal is compressed sufficiently.


Turn on the power and test the luminaire.




Moby Square LED (


Exterior LED Wall Light

Available finish: - Anthracite Only





Mounting Plate



Lamp Details

9W LED Non Replaceable Module 3000k Warm White CRI Ra:82 850 Lumens

KSR Lighting Aftersales: 023 92 674343

E-mail: info@ksr-lighting.co.uk

