Read these instructions before commencing installation. Please give these instructions to the owner/occupier after installation to retain for future reference/maintainence.

## IP20 ⊕ KK (€ (≩ 240VAC~50Hz 5A

## Important Information

Pro single circuit track luminaires only. Any damaged parts should be replaced as soon as possible complies to current IEE wiring regulations & local building control. These products are designed for use with the Escala KSR will not accept responsibility for any claims arising from a sub-standard installation. It is recommended that the track system is installed and fitted by a qualified electrician ensuring the installation

## Important User Advice

Always switch off mains supply before installing or servicing. This product is designed to be used indoors only.

## Installation Procedure

Fix the mounting bracket (Fig. 1) to the ceiling using suitable fixings for the ceiling construction. Familiarize yourself with the way the luminaire installs into the surface plate, paying particular attention to the locking tab

Connect the cables to the lighting circuit (Brown - Live, Blue - Neutral, Green/Yellow - Earth).

Fit the plate to surface plate to the mounting bracket using the screws provided.

Install your chosen Escala Pro luminaire into the surface plate, ensuring the locking tab is locked into place. Switch on mains supply and test.



Available Finishes: White or Black









KSR Lighting Ltd, Unit E Hazleton Interchange, Lakesmere Road, Horndean, Hampshire, PO8 9JU

KSR Lighting Aftersales: 023 92 674343 E-mail: aftersales@ksrlighting.com

Drg No. KSR6511-IS-B